


Steps for full reset (all clear)



Initializes various setting data & sales data, and reset vending machine's microcontroller to factory default setting.

- | | | Digital display | Remote control display |
|----------|------------------------------------|-----------------|------------------------|
| 1 | モード
Press Mode | | |
| | Screen for entering mode number | | |
| 2 | アップ
(ダウン)
Press UP & DOWN | | |
| | Set mode | | |
| 3 | 書込み
Press Confirmation | | |
| | confirm mode number | | |
| 4 | アップ
(ダウン)
Press UP & DOWN | | |
| | Set item | | |
| 5 | 書込み
Press Confirmation | | |
| | Please enter code | | |
| 6 | アップ
(ダウン)
Press UP & DOWN | | |
| | Set PIN number | | |
| 7 | 書込み
Press Confirmation | | |
| | Confirm PIN number | | |
| 8 | 終了
Press End | | |
| | System is returned to STANDBY mode | | |

: blinking

Full reset (all clear)

Note

- Data to be cleared in this procedure

1. Total (period) sales volume & amount
2. Column Sales volume & amount
3. Sales volume & amount by group
4. Sales volume & amount by price
5. Test sales volume
6. Roulette volume & amount
7. Total discount volume & amount
8. Sales downtime/column during setup
9. Data setting for alternative column
10. Cash price
11. Card price
12. Data setting for group column
13. Replenishment quantity
14. Discounted volume & column
15. Discounted amount
16. School time time zone
17. School time weekdays pattern
18. FL lamp power saving time zone
19. Cooling unit power saving time zone
20. Bill validator restriction time zone
21. FL lamp time zone
22. Time sales time zone
23. Product code
24. Coin change adjustment
25. Sold Out column when stocks is zero
26. Number of days for heating
27. Selection button number

- Data to be preset in this procedure

- ① Column-Selection setting data → Pattern 1 to 4 are reset to the factory default data。
- ② Sales halt mode → Do not set automatically
- ③ Bulk buying → 1
- ④ Digital display → Do not display
- ⑤ Automatic money return time → Unlimited
- ⑥ Column fan control setting → Control the fan
- ⑦ "sold out" when remaining stock is 0 → Do not set
- ⑧ Number of coins change adjustment → Automatic tube
- ⑨ Coins change adjustment mode → No change adjustment
- ⑩ Column transition when sales reservations → Automatic transition